

Changed files

- clients.conf
- proxy.conf
- sites-available → govroam
- mods-available → govroam_logs

Delete any other links in the sites-enabled directory ('status' can be left/added if you're allowing status checks). Attempting to run 'govroam' and 'default' will likely result in problems stating the RADIUS server.

clients.conf:

```
# Configure the JISC NRPS as a client as it will be sending request from
your people abroad.

client NAS {
    secret = something
    ipaddr = 10.10.20.1
}

client roaming0 {
    secret = something
    ipaddr = 192.168.0.1
}

# Configure your local IdP as a client. (Omit for Visited Only ORPS)
client localidp1 {
    secret = something
    ipaddr = 10.10.10.31
}
```

proxy.conf:

```
# Blackhole (REJECT) where the realm is missing.

realm NULL {
}

# Realms that don't match any other listed send to the pool of govroam
servers
realm "~.+$" {
    auth_pool = govroam
    nostrip
}

# Pool of govroam servers
home_server_pool govroam {
```

```
        home_server = roaming0
        type = client-port-balance
    }

#Govroam server configuration
home_server roaming0 {
    ipaddr = roaming0.govroam.uk
    port = 1812
    type = auth
    secret = something
    status_check = status-server # Checks status of govroam server
}

# Handle requests for the realm 'localnet'. (Omit for Visited Only ORPS)
realm localnet {
    nostrip
    auth_pool = ad_auth
}

server_pool ad_auth {
    type = client-port-balance
    home_server = localidp1
}

home_server localidp1 {
    status_check = status-server
    ipaddr = 10.10.10.31
    secret = something
    port = 1812
    type = auth
}
```

sites-available->govroam:

```
server govroam {
    # Listen on the default port on all IP addresses
    listen {
        type = auth
        ipaddr = *
    }

    authorize {
        preprocess
        update request {
            Operator-Name := 1your.domain # Adds the Operator
Name attribute to the request.
        }
        auth_log
    }
}
```

```
        suffix # Identifies the realm
              files
    }

    authenticate {
    }

    preacct {
        preprocess
        suffix
    }

    accounting {
        detail
    }

    post-auth {
        # Lots of logging
        reply_log
        f_ticks
        govroam_log
        Post-Auth-Type REJECT {
            attr_filter.access_reject
            reply_log
            f_ticks
        }
    }

    pre-proxy {
        pre_proxy_log
        if("%{Packet-Type}" != "Accounting-Request") {
            attr_filter.pre-proxy
        }
    }

    post-proxy {
        post_proxy_log
        attr_filter.post-proxy
    }
}
```

And then create a symlink from sites-enabled/govroam to sites-available/govroam.

mods-available->govroam_logs:

```
# F-TICKS
linelog f_ticks {
    filename = syslog
    format = ""
}
```

```
reference = "f_ticks.%{%reply:Packet-Type}: -format}"
f_ticks {
    Access-Accept = "F-
TICKS/govroam/1.0#REALM=%{Realm}#VISCOUNTRY=GB#VISINST=%{Operator-
Name}#CSI=%{Calling-Station-Id}#RESULT=OK#"
    Access-Reject = "F-
TICKS/govroam/1.0#REALM=%{Realm}#VISCOUNTRY=GB#VISINST=%{Operator-
Name}#CSI=%{Calling-Station-Id}#RESULT=FAIL#"
}
}

linelog govroam_log {
    filename = syslog
    format = ""
    reference = "govroam_log.%{%reply:Packet-Type}: -format}"
    govroam_log {
        Access-Accept = "govroam-auth#ORG=%{request:Realm}#USER=%{User-
Name}#CSI=%{%{Calling-Station-Id}:-Unknown Caller Id}#NAS=%{%{Called-
Station-Id}:-Unknown Access Point}#CUI=%{%{reply:Chargeable-User-Identity}:-
Unknown}#MSG=%{%{EAP-Message}:-No EAP Message}#RESULT=OK#"
        Access-Reject = "govroam-auth#ORG=%{request:Realm}#USER=%{User-
Name}#CSI=%{%{Calling-Station-Id}:-Unknown Caller Id}#NAS=%{%{Called-
Station-Id}:-Unknown Access Point}#CUI=%{%{reply:Chargeable-User-Identity}:-
Unknown}#MSG=%{%{reply:Reply-Message}:-No Failure Reason}#RESULT=FAIL#"
    }
}
```

And then create a symlink from mods-enabled/govroam_logs to mods-available/govroam_logs.

From: <https://wiki.govroam.uk/> - Govroam

Permanent link: https://wiki.govroam.uk/doku.php?id=siteadmin:basic_freeradius_orps_configuration&rev=1538474553

Last update: 2018/10/02 10:02

