

Setting Operator-Name in Clearpass

The Operator-Name attribute is used to identify the Visited Site to the Home Site. i.e. when a user joins at a Visited Site the name of the site is passed through in a RADIUS Request to the Home Site. The Home Site might use this information to generate statistics on where its users are visiting or to report problems with the Visited Site.

Setting the Operator-Name in Clearpass is impossible if your configuration uses a \\RADIUS Proxy Service to proxy unknown requests to the Jisc NRPS but easy if you use the \\RADIUS Enforcement (Generic) Service with the NRPS as Authentication Sources.

Below the configuration assumes the use of a \\RADIUS Enforcement (Generic) Service because that's the only way that Clearpass will allow attributes to be added to the Access Request.

Authentication Source

The assumption is that there is a Service which has Jisc's NRPS as the authentication sources:

Configuration > Services > Add

Services

	Service	Authentication	Roles	Enforcement	Summary
Authentication Methods:	<div style="border: 1px solid #ccc; padding: 5px; margin-bottom: 10px;"> </div> <div style="border: 1px solid #ccc; padding: 5px; margin-bottom: 10px;"> Move Up ↑ Move Down ↓ Remove View Details Modify </div> <div style="border: 1px solid #ccc; padding: 2px 10px; margin-bottom: 5px;">--Select to Add--</div>				
Authentication Sources:	<div style="border: 1px solid #ccc; padding: 5px; margin-bottom: 10px;"> NRPS [RADIUS/RadSec Server] Move Up ↑ Move Down ↓ Remove View Details Modify </div> <div style="border: 1px solid #ccc; padding: 5px; margin-bottom: 10px;"> --Select to Add-- </div>				
Strip Username Rules:	<input type="checkbox"/> Enable to specify a comma-separated list of rules to strip username				
Service Certificate:	<div style="border: 1px solid #ccc; padding: 2px 10px; margin-bottom: 5px;">--Select to Add--</div>				

Then the Source (or Sources) need to be configured to add the Operator-Name Attribute:

Summary	General	Primary	Attributes	Backup 1	Backup 2	Backup 3
Port:	1812					
Secret:	*****					
Backup 2:						
Server Name:	roaming2.govroam.uk					
Protocol:	RADIUS					
Port:	1812					
Secret:	*****					
Backup 3:						
Server Name:	roaming3.govroam.uk					
Protocol:	RADIUS					
Port:	1812					
Secret:	*****					
Attributes:						
Delete RADIUS Proxy Attributes						
Type	Name					
Add RADIUS Prox Proxy Attributes						
Type	Name			Value		
L Radius: IETF	Operator-Name	=	lacerblik.gov.uk			
RADIUS Peer Proxy Attributes						
Type	Name	Enabled as Rule				
<input type="button" value="Clear Cache"/> <input type="button" value="Copy"/> <input type="button" value="Save"/> <input type="button" value="Cancel"/>						

with the identifier for your site. Please use your realm, the primary if you have more than one. The format is 1<realm>. The '1' just means that there's a string to follow. So, if your realm is holby,nhs,uk then your Operator-Name value would be 1holby.nhs.uk

From:
<https://wiki.govroam.uk/> - **Govroam**



Permanent link:
https://wiki.govroam.uk/doku.php?id=siteadmin:clearpass_-_setting_o-n

Last update: **2024/05/15 13:08**